

40Gb/s 10km QSFP+ Transceiver Hot Pluggable, Duplex LC Connector, Single mode

Features:

- ✧ 4 CWDM lanes MUX/DEMUX design
- ✧ Up to 11.2Gbps per channel bandwidth
- ✧ Aggregate bandwidth of > 40Gbps
- ✧ Duplex LC connector
- ✧ Compliant with 40G Ethernet IEEE802.3ba and 40GBASE-LR4 Standard
- ✧ QSFP MSA compliant
- ✧ Up to 10 km transmission
- ✧ Compliant with QDR/DDR Infiniband data rates
- ✧ Single +3.3V power supply operating
- ✧ Temperature range 0°C to 70°C
- ✧ RoHS Compliant Part

Applications:

- ✧ Rack to rack
- ✧ Data centers Switches and Routers
- ✧ Metro networks
- ✧ Switches and Routers
- ✧ 40G BASE-LR4 Ethernet Links

Description:

The 40Gb/s 10km QSFP+ Transceiver is a transceiver module designed for 10Km optical communication applications. The design is compliant to 40GBASE-LR4 of the IEEE P802.3ba standard. The module converts 4 inputs channels (ch) of 10Gb/s electrical data to 4 CWDM optical signals, and multiplexes them into a single channel for 40Gb/s optical transmission. Reversely, on the receiver side, the module optically de-multiplexes a 40Gb/s input into 4 CWDM channels signals, and converts them to 4 channel output electrical data.

The central wavelengths of the 4 CWDM channels are 1271, 1291, 1311 and 1331 nm as members of the CWDM wavelength grid defined in ITU-T G694.2. It contains a duplex LC connector for the optical interface and a 38-pin connector for the electrical interface. To minimize the optical dispersion in the long-haul system, single-mode fiber (SMF) has to be applied in this module.

The product is designed with form factor, optical/electrical connection and digital diagnostic interface according to the QSFP Multi-Source Agreement (MSA). It has been designed to meet the harshest external operating conditions including temperature, humidity and EMI interference.

40Gb/s 10km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

The module operates from a single +3.3V power supply and LVCMOS/LVTTL global control signals such as Module Present, Reset, Interrupt and Low Power Mode are available with the modules. A 2-wire serial interface is available to send and receive more complex control signals and to obtain digital diagnostic information. Individual channels can be addressed and unused channels can be shut down for maximum design flexibility.

The transceiver is designed with form factor, optical/electrical connection and digital diagnostic interface according to the QSFP Multi-Source Agreement (MSA). It has been designed to meet the harshest external operating conditions including temperature, humidity and EMI interference. The module offers very high functionality and feature integration, accessible via a two-wire serial interface.

● **Absolute Maximum Ratings**

| Parameter | Symbol | Min. | Typical | Max. | Unit |
|---------------------|---------------------|------|---------|------|------|
| Storage Temperature | T _S | -40 | | +85 | °C |
| Supply Voltage | V _{CC,T,R} | -0.5 | | 4 | V |
| Relative Humidity | RH | 0 | | 85 | % |

● **Recommended Operating Environment:**

| Parameter | Symbol | Min. | Typical | Max. | Unit |
|----------------------------|---------------------|-------|---------|-------|------|
| Case operating Temperature | T _C | 0 | | +70 | °C |
| Supply Voltage | V _{CC,T,R} | +3.13 | 3.3 | +3.47 | V |
| Supply Current | I _{CC} | | | 1000 | mA |
| Power Dissipation | PD | | | 3.5 | W |

● **Electrical Characteristics (T_{OP} = 0 to 70 °C, VCC = 3.13 to 3.47 Volts)**

| Parameter | Symbol | Min | Typ | Max | Unit | Note |
|---------------------------------------|-----------------|-----|---------|-----------------|------|------|
| Data Rate per Channel | | - | 10.3125 | 11.2 | Gbps | |
| Power Consumption | | - | 2.5 | 3.5 | W | |
| Supply Current | I _{CC} | | 0.75 | 1.0 | A | |
| Control I/O Voltage-High | V _{IH} | 2.0 | | V _{CC} | V | |
| Control I/O Voltage-Low | V _{IL} | 0 | | 0.7 | V | |
| Inter-Channel Skew | T _{SK} | | | 150 | Ps | |
| RESETL Duration | | | 10 | | Us | |
| RESETL De-assert time | | | | 100 | ms | |
| Power On Time | | | | 100 | ms | |
| Transmitter | | | | | | |
| Single Ended Output Voltage Tolerance | | 0.3 | | 4 | V | 1 |
| Common mode Voltage Tolerance | | 15 | | | mV | |
| Transmit Input Diff Voltage | V _I | 150 | | 1200 | mV | |

40Gb/s 10km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

| | | | | | | |
|---------------------------------------|-------|-----|-----|-----|----|---|
| Transmit Input Diff Impedance | ZIN | 85 | 100 | 115 | | |
| Data Dependent Input Jitter | DDJ | | 0.3 | | UI | |
| Receiver | | | | | | |
| Single Ended Output Voltage Tolerance | | 0.3 | | 4 | V | |
| Rx Output Diff Voltage | Vo | 370 | 600 | 950 | mV | |
| Rx Output Rise and Fall Voltage | Tr/Tf | | | 35 | ps | 1 |
| Total Jitter | TJ | | 0.3 | | UI | |

Note:

1. 20~80%

● **Optical Parameters(TOP = 0 to 70 °C, VCC = 3.0 to 3.6 Volts)**

| Parameter | Symbol | Min | Typ | Max | Unit | Ref. |
|---|--------|------------------------------------|------|--------|-------|------|
| Transmitter | | | | | | |
| Wavelength Assignment | L0 | 1264.5 | 1271 | 1277.5 | nm | |
| | L1 | 1284.5 | 1291 | 1297.5 | nm | |
| | L2 | 1304.5 | 1311 | 1317.5 | nm | |
| | L3 | 1324.5 | 1331 | 1337.5 | nm | |
| Side-mode Suppression Ratio | SMSR | 30 | - | - | dB | |
| Total Average Launch Power | PT | - | - | 8.3 | dBm | |
| Average Launch Power, each Lane | | -7 | - | 2.3 | dBm | |
| Difference in Launch Power between any two Lanes (OMA) | | - | - | 6.5 | dB | |
| Optical Modulation Amplitude, each Lane | OMA | -4 | | +3.5 | dBm | |
| Launch Power in OMA minus Transmitter and Dispersion Penalty (TDP), each Lane | | -4.8 | - | | dBm | |
| TDP, each Lane | TDP | | | 2.3 | dB | |
| Extinction Ratio | ER | 3.5 | - | - | dB | |
| Transmitter Eye Mask Definition {X1, X2, X3, Y1, Y2, Y3} | | {0.25, 0.4, 0.45, 0.25, 0.28, 0.4} | | | | |
| Optical Return Loss Tolerance | | - | - | 20 | dB | |
| Average Launch Power OFF Transmitter, each Lane | Poff | | | -30 | dBm | |
| Relative Intensity Noise | Rin | | | -128 | dB/HZ | 1 |
| Optical Return Loss Tolerance | | - | - | 12 | dB | |
| Receiver | | | | | | |

40Gb/s 10km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

| | | | | | | |
|--|------------------|-------|---|-------|-----|---|
| Damage Threshold | THd | 3.3 | | | dBm | 1 |
| Average Power at Receiver Input, each Lane | R | -13.7 | | 2.3 | dBm | |
| Receiver Power (OMA), each Lane | | | | 3.5 | dB | |
| Receive Electrical 3 dB upper Cut off Frequency, each Lane | | | | 12.3 | GHz | |
| RSSI Accuracy | | -2 | | 2 | dB | |
| Receiver Reflectance | Rrx | | | -26 | dB | |
| Receiver Power (OMA), each Lane | | - | - | 3.5 | dBm | |
| Stressed Receiver Sensitivity in OMA, each Lane | | - | - | -9.9 | dBm | |
| Receiver Sensitivity, each Lane | SR | - | - | -11.5 | dBm | |
| Difference in Receive Power between any two Lanes (OMA) | | | | 7.5 | dB | |
| Receive Electrical 3 dB upper Cutoff Frequency, each Lane | | | | 12.3 | GHz | |
| LOS De-Assert | LOS _D | | | -15 | dBm | |
| LOS Assert | LOS _A | -30 | | | dBm | |
| LOS Hysteresis | LOS _H | 0.5 | | | dB | |

Note

1. 12dB Reflection

● **Timing for Soft Control and Status Functions**

| Parameter | Symbol | Max | Unit | Conditions |
|--------------------------------|-------------------------|------|------|---|
| Initialization Time | t _{init} | 2000 | ms | Time from power on1, hot plug or rising edge of Reset until the module is fully functional2 |
| Reset Init Assert Time | t _{reset_init} | 2 | μs | A Reset is generated by a low level longer than the minimum reset pulse time present on the ResetL pin. |
| Serial Bus Hardware Ready Time | t _{serial} | 2000 | ms | Time from power on1 until module responds to data transmission over the 2-wire serial bus |
| Monitor Data Ready Time | t _{data} | 2000 | ms | Time from power on1 to data not ready, bit 0 of Byte 2, deasserted and IntL asserted |
| Reset Assert Time | t _{reset} | 2000 | ms | Time from rising edge on the ResetL pin until the module is fully functional2 |
| LPMMode Assert Time | ton_LPMMode | 100 | μs | Time from assertion of LPMMode (Vin:LPMMode =Vih) until module power consumption enters lower Power Level |
| IntL Assert Time | ton_IntL | 200 | ms | Time from occurrence of condition |

40Gb/s 10km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

| | | | | |
|--|--------------|-----|----|--|
| | | | | triggering IntL until Vout:IntL = Vol |
| IntL Deassert Time | toff_IntL | 500 | μs | toff_IntL 500 μs Time from clear on read ³ operation of associated flag until Vout:IntL = Voh. This includes deassert times for Rx LOS, Tx Fault and other flag bits. |
| Rx LOS Assert Time | ton_los | 100 | ms | Time from Rx LOS state to Rx LOS bit set and IntL asserted |
| Flag Assert Time | ton_flag | 200 | ms | Time from occurrence of condition triggering flag to associated flag bit set and IntL asserted |
| Mask Assert Time | ton_mask | 100 | ms | Time from mask bit set ⁴ until associated IntL assertion is inhibited |
| Mask De-assert Time | toff_mask | 100 | ms | Time from mask bit cleared ⁴ until associated IntL operation resumes |
| ModSelL Assert Time | ton_ModSelL | 100 | μs | Time from assertion of ModSelL until module responds to data transmission over the 2-wire serial bus |
| ModSelL Deassert Time | toff_ModSelL | 100 | μs | Time from deassertion of ModSelL until the module does not respond to data transmission over the 2-wire serial bus |
| Power_override or Power-set Assert Time | ton_Pdown | 100 | ms | Time from P_Down bit set ⁴ until module power consumption enters lower Power Level |
| Power_override or Power-set De-assert Time | toff_Pdown | 300 | ms | Time from P_Down bit cleared ⁴ until the module is fully functional ³ |

Note:

1. Power on is defined as the instant when supply voltages reach and remain at or above the minimum specified value.
2. Fully functional is defined as IntL asserted due to data not ready bit, bit 0 byte 2 de-asserted.
3. Measured from falling clock edge after stop bit of read transaction.
4. Measured from falling clock edge after stop bit of write transaction.

40Gb/s 10km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

● Transceiver Block Diagram



● Pin Assignment




Diagram of Host Board Connector Block Pin Numbers and Name

● Pin Description

| Pin | Logic | Symbol | Name/Description | Ref. |
|-----|-------|--------|--------------------------------------|------|
| 1 | | GND | Ground | 1 |
| 2 | CML-I | Tx2n | Transmitter Inverted Data Input | |
| 3 | CML-I | Tx2p | Transmitter Non-Inverted Data output | |
| 4 | | GND | Ground | 1 |
| 5 | CML-I | Tx4n | Transmitter Inverted Data Output | |
| 6 | CML-I | Tx4p | Transmitter Non-Inverted Data Output | |
| 7 | | GND | Ground | 1 |

40Gb/s 10km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

| | | | | |
|----|-------------|---------|--------------------------------------|---|
| 8 | LVTTL-I | ModSelL | Module Select | |
| 9 | LVTTL-I | ResetL | Module Reset | |
| 10 | | VccRx | +3.3V Power Supply Receiver | 2 |
| 11 | LVC MOS-I/O | SCL | 2-Wire Serial Interface Clock | |
| 12 | LVC MOS-I/O | SDA | 2-Wire Serial Interface Data | |
| 13 | | GND | Ground | 1 |
| 14 | CML-O | Rx3p | Receiver Inverted Data Output | |
| 15 | CML-O | Rx3n | Receiver Non-Inverted Data Output | |
| 16 | | GND | Ground | 1 |
| 17 | CML-O | Rx1p | Receiver Inverted Data Output | |
| 18 | CML-O | Rx1n | Receiver Non-Inverted Data Output | |
| 19 | | GND | Ground | 1 |
| 20 | | GND | Ground | 1 |
| 21 | CML-O | Rx2n | Receiver Inverted Data Output | |
| 22 | CML-O | Rx2p | Receiver Non-Inverted Data Output | |
| 23 | | GND | Ground | 1 |
| 24 | CML-O | Rx4n | Receiver Inverted Data Output | |
| 25 | CML-O | Rx4p | Receiver Non-Inverted Data Output | |
| 26 | | GND | Ground | 1 |
| 27 | LVTTL-O | ModPrsL | Module Present | |
| 28 | LVTTL-O | IntL | Interrupt | |
| 29 | | VccTx | +3.3V Power Supply Transmitter | 2 |
| 30 | | Vcc1 | +3.3V Power Supply | 2 |
| 31 | LVTTL-I | LPMODE | Low Power Mode | |
| 32 | | GND | Ground | 1 |
| 33 | CML-I | Tx3p | Transmitter Inverted Data Output | |
| 34 | CML-I | Tx3n | Transmitter Non-Inverted Data Output | |
| 35 | | GND | Ground | 1 |
| 36 | CML-I | Tx1p | Transmitter Inverted Data Output | |
| 37 | CML-I | Tx1n | Transmitter Non-Inverted Data Output | |
| 38 | | GND | Ground | 1 |

Notes:

1. GND is the symbol for single and supply(power) common for QSFP modules, All are common within the QSFP module and all module voltages are referenced to this potential otherwise noted. Connect these directly to the host board signal common ground plane. Laser output disabled on TDIS >2.0V or open, enabled on TDIS <0.8V.
2. VccRx, Vcc1 and VccTx are the receiver and transmitter power suppliers and shall be applied concurrently. Recommended host board power supply filtering is shown below. VccRx, Vcc1 and VccTx may be internally connected within the QSFP transceiver module in any combination. The connector pins are each rated for maximum current of 500mA.

40Gb/s 10km QSFP+ Transceiver
Hot Pluggable, Duplex LC Connector, Single mode

● Recommended Circuit

